PQ	POWC4020	EN
1	APPLICATION	2
2	DESCRIPTION (FIG. A)	2
3	PACKAGE CONTENT LIST	2
4	SYMBOLS	3
5	GENERAL POWER TOOL SAFETY WARNINGS	3
5.1	Work area	3
5.2	Electrical safety	3
5.3	Personal safety	3
5.4	Power tool use and care	
5.5	Service	4
6	ADDITIONAL SAFETY-HINTS FOR SANDERS	4
7	DUST EXTRACTION	5
8	OPERATING INSTRUCTIONS	5
8.1	Switching On-off	5
8.2	Attaching the sandpaper	5
8.3	Attaching the dust bag	5
9	TECHNICAL DATA	5
10	NOISE	6
11	CLEANING AND MAINTENANCE	6
12	SERVICE DEPARTMENT	6
13	STORAGE	6
14	WARRANTY	6
15	ENVIRONMENT	7
16	DECLARATION OF CONFORMITY	Ω

EN

# HANDPALM SANDER 140W POWC4020

#### 1 APPLICATION

The sander is used to sand and buff wood, plastic and similar materials. It is very important to use the correct sandpaper!!!! It is not designed for commercial use.



WARNING! Read this manual and the general safety instructions carefully before using the machine, for your own safety. Your power tool should only be passed on together with these instructions.

# 2 DESCRIPTION (FIG. A)

- 1. Sanding disk
- 2. On/off switch
- 3. Dust extractor connection
- 4. Dust bag
- 5. Cable

### 3 PACKAGE CONTENT LIST

- Remove all packing materials
- Remove remaining packaging and transit supports (if existing)
- Check the completeness of the packing content
- Check the appliance, the power cord, the power plug and all accessories for transportation damages.
- Keep the packaging materials as far as possible till the end of the warranty period.
   Dispose it into your local waste disposal system afterwards.



WARNING Packing materials are no toys! Children must not play with plastic bags! Danger of suffocation!

1pcs handpalm sander 140W

- 1 x sanding papers (240gr)
- 1 x Dust bag
- 1 x manual



When parts are missing or damaged, please contact your dealer.




**POWC4020** 

EN

#### 4 SYMBOLS

In this manual and/or on the machine the following symbols are used:



#### 5 GENERAL POWER TOOL SAFETY WARNINGS

Read all safety warnings and all instructions. Failure to follow all warnings and instructions may result in electric shock, fire and/or serious injury. Save all warnings and instructions for future reference. The term "power tool" in the warnings refers to your mains operated (corded) power tool or battery operated (cordless) power tool.

#### 5.1 Work area

- Keep work area clean and well lit. Cluttered and dark areas invite accidents.
- Do not operate power tools in explosive atmospheres, such as in the presence of flammable liquids, gases or dust. Power tools create sparks which may ignite the dust or fumes
- Keep children and bystanders away while operating a power tool. Distractions can cause you to lose control.

#### 5.2 Electrical safety

- Power tool plugs must match the outlet. Never modify the plug in any way. Do not use any adapter plugs with earthed (grounded) power tools. Unmodified plugs and matching outlets will reduce risk of electric shock.
- Avoid body contact with earthed or grounded surfaces such as pipes, radiators, ranges and refrigerators. There is an increased risk of electric shock if your body is earthed or grounded.
- Do not expose power tools to rain or wet conditions. Water entering a power tool will increase the risk of electric shock.
- Do not abuse the cord. Never use the cord for carrying, pulling or unplugging the power tool. Keep cord away from heat, oil, sharp edges or moving parts. Damaged or entangled cords increase the risk of electric shock.
- When operating a power tool outdoors, use an extension cord suitable for outdoor use.
   Use of a cord suitable for outdoor use reduces the risk of electric shock.
- If operating a power tool in a damp location is unavoidable, use a residual current device (RCD) protected supply. Use of an RCD reduces the risk of electric shock.

## 5.3 Personal safety

- Stay alert, watch what you are doing and use common sense when operating a power tool. Do not use a power tool while you are tired or under the influence of drugs, alcohol or medication. A moment of inattention while operating power tools may result in serious personal injury.
- Use safety equipment. Always wear eye protection. Safety equipment such as dust mask, non-skid safety shoes, hard hat, or hearing protection used whenever conditions require will reduce personal injuries.

- Avoid accidental starting. Ensure the switch is in the off position before plugging in.
   Carrying power tools with your finger on the switch or plugging in power tools that have the switch on invites accidents.
- Remove any adjusting key or wrench before turning the power tool on. A wrench or a key left attached to a rotating part of the power tool may result in personal injury.
- Do not overreach. Keep proper footing and balance at all times. This enables better control of the power tool in unexpected situations.
- Dress properly. Do not wear loose clothing or jewellery. Keep your hair, clothing and gloves away from moving parts. Loose clothes, jewellery or long hair can be caught in moving parts.
- If devices are provided for the connection of dust extraction and collection facilities, ensure
  these are connected and properly used. Use of these devices can reduce dust related
  hazards.

#### 5.4 Power tool use and care

- Do not force the power tool. Use the correct power tool for your application. The correct power tool will do the job better and safer at the rate for which it was designed.
- Do not use the power tool if the switch does not turn it on and off. Any power tool that cannot be controlled with the switch is dangerous and must be repaired.
- Disconnect the plug from the power source before making any adjustments, changing accessories, or storing power tools. Such preventive safety measures reduce the risk of starting the power tool accidentally.
- Store idle power tools out of the reach of children and do not allow persons unfamiliar with the power tool or these instructions to operate the power tool. Power tools are dangerous in the hands of untrained users.
- Maintain power tools. Check for misalignment or sticking of moving parts, breakage of
  parts and any other condition that may affect the power tool's operation. If damaged, have
  the power tool repaired before use. Many accidents are caused by poorly maintained
  power tools.
- Keep cutting tools sharp and clean. Properly maintained cutting tools with sharp cutting edges are less likely to stick and are easier to control.
- Use the power tool, accessories and tool bits etc., in accordance with these instructions
  and in the manner intended for the particular type of power tool, taking into account the
  working conditions and the work to be performed. Use of the power tool for operations
  different from intended could lead to a hazardous situation.

#### 5.5 Service

 Have your power tool serviced by a qualified repair person using only identical replacement parts. This will ensure that the safety of the power tool is maintained.

#### 6 ADDITIONAL SAFETY-HINTS FOR SANDERS

- The tool may only be used for dry sanding.
- When operating the device ensure that the area you are working in is clean and tidy
- Do not leave objects or cable laying around in the vicinity of the device.
- When working with the device make sure the area is well lit.
- Secure the work piece to be processed to prevent it from slipping.
- Prevent overheating of the device and the work piece.
- Do not process any materials that contain hazardous substances. There is a risk of cancerous substances being released.
- Keep the handles dry and free of grease.
- Symbols appearing on your device may not be removed or covered. Signs on the device that are no longer legible must be replaced immediately.



# 7 DUST EXTRACTION

Dusts from materials such as lead-containing paint, some types of wood, minerals and metal may be harmful to health. Touching or inhaling the dusts can cause allergic reactions and/or ailments of the respiratory tract of the user or persons in the vicinity. Certain dusts such as oak or beech dust are considered carcinogenic, particularly in combination with wood treatment additives (chromate, wood preservatives). Materials containing asbestos may only be processed by experts.

- Always use a dust extraction facility.
- Make sure the workplace is well ventilated.
- Always wear a dust protection mask.
- Observe the regulations valid in your country for the materials to be processed.

# 8 OPERATING INSTRUCTIONS



Do not sand plaster surfaces, (WARNING: In this case your guarantee becomes void) this may clog the motor (brushes, ball bearings, ..).

#### 8.1 Switching On-off

Press On-off switch I/O (2)

## 8.2 Attaching the sandpaper

- Select sandpaper with the correct grain size. Make sure the perforations in the paper coincide with those on the sanding base plate.
- Then attach the sand paper to the sanding plate, using the hook-and-loop system of the sand paper and the sanding plate.
- The sandpaper should rest flush on the base plate and must not come loose.
- You can be sure to find the right sandpaper among our product range (see technical specifications).

#### 8.3 Attaching the dust bag

This machine is supplied with a dust bag. In the interests of your health, always use the dust bag for dust extraction when running the machine.



For even a better dust extraction of the working surface, your sanding machine can be connected to the ordinary vacuum cleaner for house-use with a dust extraction connector.

### 9 TECHNICAL DATA

Power rating	140W
Mains voltage	230-240V
Mains frequency	50Hz
Sanding surface	140 x 140 x 80mm
No load speed	13.000 min <sup>-1</sup>
Safety class	II



## **POWC4020**

EN

#### 10 NOISE

Noise emission values measured according to relevant standard. (K=3)

Acoustic pressure level LpA 77 dB(A)
Acoustic power level LwA 88 dB(A)



ATTENTION! Wear hearing protection when sound pressure is over 85 dB(A).

aw (Vibration):  $4.5 \text{m/s}^2$   $K = 1.5 \text{ m/s}^2$ 

#### 11 CLEANING AND MAINTENANCE

- The machine does not require any special maintenance.
- For safe and efficient working, always keep the machine and the ventilation slots clean.
- Always be sure that the tool is switched off and unplugged before carrying out any work on the tool.

#### 12 SERVICE DEPARTMENT

- Damaged switches must be replaced by our after-sales service department.
- If the connecting cable (or mains plug) is damaged, it must be replaced by a particular connecting cable which is available from our service department. Replacement of the connecting cable must only be carried out by our service department (see last page) or by a qualified person (qualified electrician).

#### 13 STORAGE

- Thoroughly clean the whole machine and its accessories.
- Store it out of the reach of children, in a stable and secure position, in a cool and dry place, avoid too high and too low temperatures.
- Protect it from exposure to direct sunlight. Keep it in the dark, if possible.
- Don't keep it in plastic bags to avoid humidity build-up.

#### 14 WARRANTY

- This product is warranted as provided by law for a 24 -month period effective from the date of purchase by the first user.
- This warranty covers all material or production flaws excluding: batteries, chargers, defective parts subject to normal wear & tear such as bearings, brushes, cables, and plugs, or accessories such as drills, drill bits, saw blades, etc.; damage or defects resulting from maltreatment, accidents or alterations; nor the cost of transportation.
- Damage and/or defects resulting from inappropriate use also do not fall under the warranty provisions.
- We also disclaim all liability for any bodily injury resulting from inappropriate use of the tool
- Repairs may only be carried out by an authorised customer service centre for Powerplus tools
- You can always obtain more information at the number 00 32 3 292 92 90.
- Any transportation costs shall always be borne by the customer, unless agreed otherwise in writing.
- At the same time, no claim can be made on the warranty if the damage of the device is the result of negligent maintenance or overload.



#### POWC4020

EN

- Definitely excluded from the warranty is damage resulting from fluid permeation, excessive dust penetration, intentional damage (on purpose or by gross carelessness), inappropriate usage (use for purposes for which the device is not suitable), incompetent usage (e.g. not following the instructions given in the manual), inexpert assembly, lightning strike, erroneous net voltage. This list is not exhaustive.
- Acceptance of claims under warranty can never lead to the prolongation of the warranty period nor commencement of a new warranty period in case of a device replacement.
- Devices or parts which are replaced under the warranty therefore remain the property of Varo NV.
- We reserve the right to reject a claim whenever the purchase cannot be verified or when it
  is clear that the product has not been properly maintained. (Clean ventilation slots, carbon
  brushes serviced regularly, etc.).
- Your purchase receipt must be kept as proof of date of purchase.
- Your appliance must be returned undismantled to your dealer in an acceptably clean state, (in its original blow-moulded case if applicable to the unit), accompanied by proof of purchase.

#### 15 ENVIRONMENT



Should your appliance need replacement after extended use, do not discard it with the household rubbish but dispose of it in an environmentally safe way. Waste produced by electrical machine items should not be handled like normal household rubbish. Please recycle where recycle facilities exist. Check with your Local Authority or retailer for recycling advice.

# POWERPLUS POWC4020 16 DECLARATION OF CONFORMITY





VARO N.V. - Joseph Van Instraat 9 - BE2500 Lier - BELGIUM, declares that,

Product: Handpalm Sander 140W

Trade mark: POWERplus Model: POWC4020

is in conformity with the essential requirements and other relevant provisions of the applicable European Directives, based on the application of European harmonized standards. Any unauthorized modification of the apparatus voids this declaration.

European Directives (including, if applicable, their amendments up to the date of signature);

2006/42/EC 2014/30/EC 2011/65/EU

European harmonized standards (including, if applicable, their amendments up to the date of signature);

EN60745-1: 2009 EN60745-2-4: 2009 EN55014-1: 2006 EN55014-2: 2015 EN61000-3-2: 2014 EN61000-3-3: 2013

Keeper of the Technical Documentation : Philippe Vankerkhove, VARO – Vic. Van Rompuy N.V.

The undersigned acts on behalf of the company CEO,

Philippe Vankerkhove Regulatory Affairs – Compliance Manager 12/07/18